

SW-PT smart switch for boiler/heater 16A double-pole

Model number - SW-PT

This smart module is designed for an electric boiler or heater. The switch is double-pole for live and neutral. It can be installed without changing the infrastructure and wiring.

The switch can be set as an on/off switch or as a timed switch. The configuration is done in the App when pairing the switch. The switch has four illuminated segments. Each segment indicates a half hour. Each press of the switch adds a half hour to the timer up to two hours. It is possible to turn on the switch for up to 5 hours in the App. The switch has a current sensor which protects the switch from overload. It also measures the current consumption of the switch.

Technical Information // 16A double pole switch for a boiler or heater

Power supply	100-240V 50-60 Hz
Load range	0-16A (3500VA)
Transmission frequency	MHz 433.5-434.5
Transmission range	up to 100M
Functionality	on/off, timed on
Background lighting	Shade of color and brightness can be set in the application
Current sensor	0-30A
Protections and safety	double protection: 1// Thermal fuse for protection against overheating. 2// Current sensor protection
Dimensions	height 44 mm, width 44 mm, depth 30 mm
	Compatible with a variety of decorative panels

Installation Instructions

Connect the line wire **to Lin**
Connect the neutral wire **to N**
Connect the line out wire **to Lo**
Connect the Neutral out wire **to No**

- This switch **requires** a neutral.
- This switch is a **double pole switch**.

